## **D-70** Series Weighing Indicator

The D-70 are easy-to operate indicator its economical indicator with 50mm Digit height, housed in A.B.S enclosure.

ž sang

OK

### Main Functions:

General Weighing, Animal Weighing. Peak Hold, Data Hold, Auto Hold. Accumulation. Rs 232c output. Low battery alarm. Automatically Power Off

### Technical Data:

Hi resolution Weighing Indicator.. High Quality & economical Up to 1/10,000 display resolution selectable decimal point position Interval: 1/2/5/10/20/50 6 digits 50mm LED display Low power and overload indication A.B.S Enclosure, equipped with desktop bracket Full Duplex RS-232 Serial Port Baud rate optional: 1200/2400/4800/9600 Drives up to four 350Ω load cells weight unit Kg Operates on AC 220V or Rechargeable battery DC 4V/4Ah

> It is equipped with a large easy to read 6 digits 50 mm LED display. A full duplex RS-232 port can transmit data on demand or continuously to match the input requirement of a wide variety of devices including printers. Remote displays and computers. Rechargeable battery or AC 220V operated.

D-70

## **Economical Platform scale Indicator!**

# **D-70 Series Weighing Indicator**


Interface:

**Physical Dimension** 

150

V

220



#### **Features:**

Hi resolution Weighing Indicator. High Quality / economical Cost Up to 1/10,000 display resolution 6 digits 50mm LED display Low power and overload indication A.B.S Enclosure, equipped with desktop bracket Full Duplex RS-232 Serial Port Drives up to four  $350\Omega$  load cells weight unit Kg and selectable decimal point position Full duplex RS232 with multiple communication protocols Customized size with your specific request

### **Specifications:**

Input sensitivity: Input single range: Load cell excitation: Stabilization time: Operating temperature: Non-linearity: A/D resolution: keys: Maximum Display: Minimum Division: Under zero Indication: **Display Indications :** Battery: Power:

 $0.1\mu V//d(Min)$ 0~12.8mv 3.3VDC 50mA 1 second typical 0° c ~ 50° c / 32° F~ 122° F 0.01% of F.S 3000e "on/off", "Total", "Hold", "Tare", "Zero", "Set" 999999 1 X 2 X 5 X 10 X 20 X 50. "-" minus display Hi, Ok, Lo, Battery Charging, Hold, Auto, Net, Gross, Tare & Total 4V DC/4Ah

Reliable and Rugged!

220V AC 50 Hz



85

172

0 🗌 0

୍

୍